

Cisco Gigabit Ethernet Transceiver Modules Compatibility Matrix

Revised: October 7, 2014

Note—Requirements and procedures for initial configurations and software upgrades tend to change and therefore appear only in the switch or router software release notes. Before installing, configuring, or upgrading a switch, refer to the product release notes on Cisco.com for the latest information. This matrix does not replace or supersede the release notes.

This publication contains information on the Cisco platforms and minimum software releases that support the Gigabit Interface Converter (GBIC) and Gigabit Ethernet Small Form-Factor Pluggable (SFP) transceiver modules. Table 1 lists the Gigabit Ethernet transceiver model numbers and operating wavelengths. The other tables are as follows:

- Table 2 , Catalyst Express 500 Support
- Table 3 , Metro Ethernet Support
- Table 4 , Catalyst 2900 Switches Support
- Table 5 , Catalyst 3500 Switches Support
- Table 6 , Catalyst 3600 Series Switches Support
- Table 7 , Catalyst 3700 Series Switches Support
- Table 8 , Catalyst 3800 Series Switches Support
- Table 9 , Industrial Ethernet and Smart Grid Support
- Table 10 , Catalyst 4500 and Catalyst 4900 Switches Support
- Table 11 , Catalyst 6500 Series Switches Support
- Table 12 , Catalyst 6800 Series Switches Support
- Table 13 , Data Center and Blade Switching Support
- Table 14 , Router Support
- Table 15 , Appliance Support
- Table 16 , Wireless LAN Controllers Support

Table 1 Gigabit Ethernet Transceiver Models	
Model Number	Description

GBIC Transceivers	
WS-G5482=	1000BASE-T GBIC transceiver module for Category 5 copper wire, RJ-45 connector
WS-G5483=	1000BASE-T GBIC transceiver module for Category 5 copper wire, RJ-45 connector
WS-G5484=	1000BASE-SX GBIC transceiver module for Multi mode Fiber (MMF), 850-nanometer (nm) wavelength, dual SC/PC connector
WS-G5486=	1000BASE-LX/LH GBIC transceiver module for MMF and SMF, 1300-nm wavelength, dual SC/PC connector
WS-G5487=	1000BASE-ZX GBIC transceiver module for Single Mode Fiber (SMF), 1550-nm wavelength, dual SC/PC connector
CWDM GBIC Transceivers (Dual SC/PC connectors)	
CWDM-GBIC-1470=	Cisco 1000BASE-CWDM GBIC 1470 nm
CWDM-GBIC-1490=	Cisco 1000BASE-CWDM GBIC 1490 nm
CWDM-GBIC-1510=	Cisco 1000BASE-CWDM GBIC 1510 nm
CWDM-GBIC-1530=	Cisco 1000BASE-CWDM GBIC 1530 nm
CWDM-GBIC-1550=	Cisco 1000BASE-CWDM GBIC 1550 nm
CWDM-GBIC-1570=	Cisco 1000BASE-CWDM GBIC 1570 nm
CWDM-GBIC-1590=	Cisco 1000BASE-CWDM GBIC 1590 nm
CWDM-GBIC-1610=	Cisco 1000BASE-CWDM GBIC 1610 nm
DWDM GBIC Transceivers (Dual SC/PC connectors)	
DWDM-GBIC-60.61=	1000BASE-DWDM GBIC 1560.61 nm
DWDM-GBIC-59.79=	1000BASE-DWDM GBIC 1559.79 nm
DWDM-GBIC-58.98=	1000BASE-DWDM GBIC 1558.98 nm

DWDM- GBIC- 58.17=	1000BASE-DWDM GBIC 1558.17 nm
DWDM- GBIC- 56.55=	1000BASE-DWDM GBIC 1556.55 nm
DWDM- GBIC- 55.75=	1000BASE-DWDM GBIC 1555.75 nm
DWDM- GBIC- 54.94=	1000BASE-DWDM GBIC 1554.94 nm
DWDM- GBIC- 54.13=	1000BASE-DWDM GBIC 1554.13 nm
DWDM- GBIC- 52.52=	1000BASE-DWDM GBIC 1552.52 nm
DWDM- GBIC- 51.72=	1000BASE-DWDM GBIC 1551.72 nm
DWDM- GBIC- 50.92=	1000BASE-DWDM GBIC 1550.92 nm
DWDM GBIC Transceivers (continued)	
DWDM- GBIC- 50.12=	1000BASE-DWDM GBIC 1550.12 nm
DWDM- GBIC- 48.51=	1000BASE-DWDM GBIC 1548.51 nm
DWDM- GBIC- 47.72=	1000BASE-DWDM GBIC 1547.72 nm
DWDM- GBIC- 46.92=	1000BASE-DWDM GBIC 1546.92 nm
DWDM- GBIC- 46.12=	1000BASE-DWDM GBIC 1546.12 nm
DWDM-	1000BASE-DWDM GBIC 1544.53 nm

GBIC-44.53=	
DWDM-GBIC-43.73=	1000BASE-DWDM GBIC 1543.73 nm
DWDM-GBIC-42.94=	1000BASE-DWDM GBIC 1542.94 nm
DWDM-GBIC-42.14=	1000BASE-DWDM GBIC 1542.14 nm
DWDM-GBIC-40.56=	1000BASE-DWDM GBIC 1540.56 nm
DWDM-GBIC-39.77=	1000BASE-DWDM GBIC 1539.77 nm
DWDM-GBIC-39.98=	1000BASE-DWDM GBIC 1539.98 nm
DWDM-GBIC-38.19=	1000BASE-DWDM GBIC 1538.19 nm
DWDM-GBIC-35.82=	1000BASE-DWDM GBIC 1535.82 nm
DWDM-GBIC-35.04=	1000BASE-DWDM GBIC 1535.04 nm
DWDM-GBIC-34.25=	1000BASE-DWDM GBIC 1534.25 nm
DWDM-GBIC-32.68=	1000BASE-DWDM GBIC 1532.68 nm
DWDM-GBIC-31.90=	1000BASE-DWDM GBIC 1531.90 nm
DWDM-GBIC-31.12=	1000BASE-DWDM GBIC 1531.12 nm

DWDM-GBIC-30.33=	1000BASE-DWDM GBIC 1530.33 nm
SFP Transceivers	
GLC-T=	1000BASE-T SFP transceiver module for Category 5 copper wire, RJ-45 connector
GLC-SX-MM=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, dual LC/PC connector
GLC-LH-SM=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, dual LC/PC connector
GLC-ZX-SM=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, dual LC/PC connector
GLC-BX-D=	1000BASE-BX10 SFP module for single-strand SMF, 1490-nm TX/1310-nm RX wavelength, single LC/PC connector
GLC-BX-U=	1000BASE-BX10 SFP module for single-strand SMF, 1310-nm TX/1490-nm RX wavelength, single LC/PC connector
GLC-2BX-D=	Dual-channel 1000BASE-BX10 SFP module for single-strand SMF, 1490-nm TX/1310-nm RX wavelength, two single LC/PC connectors
SFP Transceivers (continued)	
SFP-GE-S=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-L=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-EX-SMD=	1000BASE-EX SFP transceiver module for SMF, 1310-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-Z=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
SFP-GE-T=	1000BASE-T SFP transceiver module for Category 5 copper wire, extended operating temperature range, RJ-45 connector
GLC-SX-MM-RGD	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, industrial Ethernet, dual LC/PC connector
GLC-LX-SM-RGD	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, industrial Ethernet, dual LC/PC connector
GLC-ZX-	1000BASE-ZX SFP transceiver module for SMF, 1550-nm

SM-RGD	wavelength, industrial Ethernet, dual LC/PC connector
GLC-SX-MMD=	1000BASE-SX SFP transceiver module for MMF, 850-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-LH-SMD=	1000BASE-LX/LH SFP transceiver module for MMF and SMF, 1300-nm wavelength, extended operating temperature range and DOM support, dual LC/PC connector
GLC-ZX-SMD=	1000BASE-ZX SFP transceiver module for SMF, 1550-nm wavelength, dual LC/PC connector
SFP-GPON-B	Gigabit passive optical network (GPON) Class B+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength
SFP-GPON-B-I	Gigabit passive optical network (GPON) Class B+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength, industrial temperature range
SFP-GPON-C	Gigabit passive optical network (GPON) Class C+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength
SFP-GPON-C-I	Gigabit passive optical network (GPON) Class C+ SFP OLT transceiver module, 1490-nm TX/1310-nm RX wavelength, industrial temperature range
CWDM SFP Transceivers (dual LC/PC connector)	
CWDM-SFP-1470=	Cisco CWDM SFP 1470 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1490=	Cisco CWDM SFP 1490 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1510=	Cisco CWDM SFP 1510 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1530=	Cisco CWDM SFP 1530 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1550=	Cisco CWDM SFP 1550 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1570=	Cisco CWDM SFP 1570 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1590=	Cisco CWDM SFP 1590 nm; Gigabit Ethernet and 1G/2G FC
CWDM-SFP-1610=	Cisco CWDM SFP 1610 nm; Gigabit Ethernet and 1G/2G FC
DWDM SFP Transceivers (dual LC/PC connector)	
DWDM-SFP-6061=	Cisco 1000BASE-DWDM SFP 1560.61 nm

DWDM-SFP-5979=	Cisco 1000BASE-DWDM SFP 1559.79 nm
DWDM-SFP-5898=	Cisco 1000BASE-DWDM SFP 1558.98 nm
DWDM-SFP-5817=	Cisco 1000BASE-DWDM SFP 1558.17 nm
DWDM-SFP-5655=	Cisco 1000BASE-DWDM SFP 1556.55 nm
DWDM-SFP-5575=	Cisco 1000BASE-DWDM SFP 1555.75 nm
DWDM-SFP-5413=	Cisco 1000BASE-DWDM SFP 1554.13 nm
DWDM-SFP-5494=	Cisco 1000BASE-DWDM SFP 1554.94 nm
DWDM-SFP-5252=	Cisco 1000BASE-DWDM SFP 1552.52 nm
DWDM-SFP-5172=	Cisco 1000BASE-DWDM SFP 1551.72 nm
DWDM-SFP-5092=	Cisco 1000BASE-DWDM SFP 1550.92 nm
DWDM-SFP-5012=	Cisco 1000BASE-DWDM SFP 1550.12 nm
DWDM-SFP-4851=	Cisco 1000BASE-DWDM SFP 1548.51 nm
DWDM-SFP-4772=	Cisco 1000BASE-DWDM SFP 1547.72 nm
DWDM-SFP-4692=	Cisco 1000BASE-DWDM SFP 1546.92 nm
DWDM-SFP-4612=	Cisco 1000BASE-DWDM SFP 1546.12 nm
DWDM-SFP-4453=	Cisco 1000BASE-DWDM SFP 1544.53 nm
DWDM-SFP-4373=	Cisco 1000BASE-DWDM SFP 1543.73 nm
DWDM-SFP-4294=	Cisco 1000BASE-DWDM SFP 1542.94 nm
DWDM-SFP-4214=	Cisco 1000BASE-DWDM SFP 1542.14 nm
DWDM-	Cisco 1000BASE-DWDM SFP 1540.56 nm

SFP-4056=	
DWDM-SFP-3977=	Cisco 1000BASE-DWDM SFP 1539.77 nm
DWDM-SFP-3898=	Cisco 1000BASE-DWDM SFP 1539.98 nm
DWDM-SFP-3819=	Cisco 1000BASE-DWDM SFP 1538.19 nm
DWDM-SFP-3661=	Cisco 1000BASE-DWDM SFP 1536.61 nm
DWDM-SFP-3582=	Cisco 1000BASE-DWDM SFP 1535.82 nm
DWDM SFP Transceivers (continued)	
DWDM-SFP-3504=	Cisco 1000BASE-DWDM SFP 1535.04 nm
DWDM-SFP-3425=	Cisco 1000BASE-DWDM SFP 1534.25 nm
DWDM-SFP-3268=	Cisco 1000BASE-DWDM SFP 1532.68 nm
DWDM-SFP-3190=	Cisco 1000BASE-DWDM SFP 1531.90 nm
DWDM-SFP-3112=	Cisco 1000BASE-DWDM SFP 1531.12 nm
DWDM-SFP-3033=	Cisco 1000BASE-DWDM SFP 1530.33 nm
DWDM SFP Transceivers (8 additional wavelengths) (dual LC/PC connector)	
DWDM-SFP-6141=	Cisco 1000BASE-DWDM SFP 1561.42 nm
DWDM-SFP-5736=	Cisco 1000BASE-DWDM SFP 1557.36 nm
DWDM-SFP-5332=	Cisco 1000BASE-DWDM SFP 1553.33 nm
DWDM-SFP-4931=	Cisco 1000BASE-DWDM SFP 1549.32 nm
DWDM-SFP-4532=	Cisco 1000BASE-DWDM SFP 1545.32 nm
DWDM-SFP-4134=	Cisco 1000BASE-DWDM SFP 1541.35 nm
DWDM-	Cisco 1000BASE-DWDM SFP 1537.40 nm

SFP-3739=	
DWDM-SFP-3346=	Cisco 1000BASE-DWDM SFP 1533.47 nm

Table 2 Catalyst Express 500 Support				
			Minimum Software Release Required	
Platform	Switch or Module	Transceiver Module	DOM Support	Cisco IOS Release
Catalyst Express 500	WS-CE500-24LC WS-CE500-24PC WS-CE500G-12TC	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(25)FY
Catalyst Express 520	WS-CE520-8PC-K9	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(35)EX
	WS-CE520-24LC-K9 WS-CE520-24PC-K9 WS-CE520G-24TC-K9	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(37)EX

Table 3 Metro Ethernet Support				
			Minimum Software Release Required	
Platform	Switch or Module	Transceiver Module	DOM Support	Cisco IOS Release
Cisco ME 2400	ME-2400-24TS-A ME-2400-24TS-D	GLC-T(10/100/1000) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	12.2(25)EX
		GLC-BX-D	12.2(44)SE	12.2(25)EX

		GLC-BX-U CDWM SFP		
Cisco ME2600X	ME2600X-44FA-D-K9= ME2600X-44FE-D-K9= ME2600X-44FA-A-K9=	GLC-BX-D GLC-BX-U	--	15.2(02)SA
Cisco ME 3400	ME-3400-24TS-A ME-3400-24TS-D	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(25)EX
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(46)SE	12.2(25)EX
		GLC-ZX-SM	12.2(46)SE	12.2(25)EX
		GLC-BX-D GLC-BX-U CDWM SFP	12.2(44)SE	12.2(25)EX
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	--	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE
Cisco ME 3400 (continued)	ME-3400G-12CS-A ME-3400G-12CS-D	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(25)SEG1
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(46)SE	12.2(25)SEG1
		GLC-ZX-SM	12.2(46)SE	12.2(25)SEG1
		GLC-BX-D	12.2(44)SE	12.2(25)SEG1
		GLC-BX-U	12.2(44)SE	12.2(25)SEG1
		CWDM SFP	12.2(44)SE	12.2(25)SEG1

		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	--	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE
	ME-3400G-2CS-A	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(35)SE1
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM	12.2(46)SE	12.2(35)SE1
		GLC-BX-D GLC-BX-U	12.2(44)SE	12.2(35)SE1
		CWDM SFP	12.2(44)SE	12.2(35)SE1
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	--	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE
	Cisco ME 3400 (continued)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(40)SE
		GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(46)SE	12.2(40)SE
		GLC-BX-D GLC-BX-U	12.2(44)SE	12.2(40)SE
		CWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP	12.2(50)SE	12.2(40)SE

		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE
		SFP-GE-T (10/100/1000)	--	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE
	ME-3400E- 24TS-M ME- 3400EG- 2CS-A ME- 3400EG- 12CS-M	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(44)EY
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(44)EY	12.2(44)EY
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-T (10/100/1000)	--	12.2(46)SE
		GLC-EX-SMD	12.2(52)SE	12.2(52)SE
		GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	--	12.1(14)AX
		GLC-ZX-SM	12.2(46)SE	12.1(14)AX1
		CWDM SFP	12.2(44)SE	12.1(14)AX1
Catalyst 3750 Metro	ME-C3750- 24TE-M	GLC-BX-D GLC-BX-U	12.2(44)SE	12.2(25)EY2
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(50)SE	12.2(50)SE
		SFP-GE-S SFP-GE-L	12.2(46)SE	12.2(46)SE

		SFP-GE-T (10/100/1000)	--	12.2(46)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-EX-SMD	12.2(52)SE	12.2(52)SE
Cisco ME 3600X	ME-3600X-24FS-M (SFP ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM SFP-GE-T (10/100/1000)	--	12.2(52)EY
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L GLC-BX-U (CPN 10-2094-02) GLC-BX-D (CPN 10-2093-02)	12.2(52)EY	12.2(52)EY
		CWDM SFP DWDM SFP DWDM SFP (add.) GLC-EX-SMD GLC-ZX-SM	15.1(2)EY	15.1(2)EY
Cisco ME 3600X (continued)	ME-3600X-24FS-M	GLC-SX-MM GLC-LH-SM	--	12.2(52)EY
	ME-3600X-24TS-M (SFP+ ports)	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(52)EY	12.2(52)EY
	ME-3600X-	SFP-GE-Z	15.3(1)S	15.3(1)S

	24CX-M	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD GLC-SX-MMD GLC-EX-SMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-L SFP-GE-S GLC-LH-SM GLC-SX-MM GLC-T SFP-GE-T GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP DWDM SFP (add.)	15.2(2)S1	15.2(2)S1
Cisco ME 3800X	ME-3800X-24FS-M (client ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM SFP-GE-T (10/100/1000)	--	12.2(52)EY
		GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(52)EY	12.2(52)EY
	ME-3800X-24FS-M (SFP+ ports)	GLC-SX-MM GLC-LH-SM	--	12.2(52)EY
		GLC-SX-MMD GLC-LH-SMD	12.2(52)EY	12.2(52)EY

		GLC-ZX-SMD GLC-ZX-SM SFP-GE-S SFP-GE-L CWDM SFP DWDM SFP DWDM SFP (add.)		
Cisco ME 4600 Series	ME4600-AMX-16GPON	SFP-GPON-B SFP-GPON-B-I SFP-GPON-C SFP-GPON-C-I	3.3.1	3.3.1
	ME4600-AMX-48GE	GLC-BX-D GLC-BX-U GLC-2BX-D	3.3.1	3.3.1
Cisco ME 4900 Series	ME-4924-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(31)SGA
		GLC-ZX-SMD GLC-BX-D GLC-BX-U CDWM SFP	12.2(31)SGA	12.2(31)SGA
		DWDM SFP	12.2(37)SG	12.2(37)SG
Cisco ME 6500 Series	ME-C6524GS-8S ME-C6524GT-8S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CDWM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	12.2(18)ZU
		GLC-T (10/100/1000)	--	12.2(33)SXH
		DWDM SFP	--	12.2(18)ZU2

Table 4 Catalyst 2900 Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release
Catalyst 2900 series	WS-C2980G-A	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2.1	--
	WS-C2948G	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2	--
	WS-C2948G-L3	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	7.2	--
	WS-C2948G-GE-TX	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD CWDM SFP	8.2(1)GLX	--
	WS-C2912MF-XL with WS-X2931-XL	WS-G5482	--	12.0(5)XW
		WS-G5483 WS-G5484 WS-G5486 WS-G5487	--	12.0(5)WC3b
		CWDM GBIC	--	12.0(5)WC5
	WS-C2924M-XL-EN with WS-X2931-XL	WS-G5483 WS-G5484 WS-G5486 WS-G5487	--	12.0(5)WC3b
		CWDM GBIC		12.0(5)WC5
	WS-C2924M-XL-EN-DC with WS-X2931-XL	WS-G5483 WS-G5484 WS-G5486	--	12.0(5)WC3b

		WS-G5487		
		CWDM GBIC	--	12.0(5)WC5
Catalyst 2940 Series	WS-C2940-8TF-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.1(13)AY
Catalyst 2950 Series	WS-C2950G-12-EI	WS-G5483 WS-G5484	--	12.1(6)EA2b
	WS-C2950G-24-EI	WS-G5486 WS-G5487		
	WS-C2950G-24-EI-DC	CWDM GBIC	--	12.1(12c)EA1
	WS-C2950G-48-EI	DWDM GBIC	--	12.1(20)EA2
	WS-C2950ST-8 LRE	GLC-T (1000BASE-T)	--	12.1(19)EA1c
	WS-C2950ST-24 LRE	GLC-SX-MM GLC-LH-SM		
	WS-C2950ST-24 LRE997	GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-SX-MMD GLC-LH-SMD		
Catalyst 2960 series	WS-C2960-24TC-L	GLC-T (1000BASE-T)	--	12.2(25)FX
	WS-C2960G-24TC-L	GLC-SX-MM GLC-LH-SM		
	WS-C2960-48TC-L	GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD		
	WS-C2960-24PC-L	GLC-T (1000BASE-T)	--	12.2(44)SE

		GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD		
	WS-C2960-24TC-S WS-C2960-48TC-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(37)EY
	WS-C2960-8TC-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(46)SE
Catalyst 2960 series (continued)	WS-C2960-48PST-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.2(46)SE
	WS-C2960-8TC-L WS-C2960G-8TC-L	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.2(35)SE

	WS-C2960G-48TC-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.2(25)SEE
	WS-C2960-48PST-S WS-C2960-24PC-S WS-C2960-24LC-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(50)SE
Catalyst 2960-Plus Series	WS-C2960+48PST-L WS-C2960+24PC-L WS-C2960+24LC-L WS-C2960+48TC-L WS-C2960+24TC-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	15.0(2)EZ
	WS-C2960+48PST-S WS-C2960+24PC-S WS-C2960+24LC-S WS-C2960+48TC-S WS-C2960+24TC-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	15.0(2)EZ
Catalyst 2960-S Series	WS-C2960S-24TS-S WS-C2960S-48TS-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	--	12.2(53)SE1

		GLC-SX-MMD GLC-LH-SM		
		GLC-EX-SMD (CPN 10-2624-01 or later only)	--	IOS 12.2(58)SE
	WS-C2960S-48FPS-L WS-C2960S-48LPS-L WS-C2960S-24PS-L WS-C2960S-48TS-L WS-C2960S-24TS-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.2(53)SE1
		GLC-EX-SMD (CPN 10-2624-01 or later only)	--	IOS 12.2(58)SE
Catalyst 2960-S Series (continued)	WS-C2960S-48FPD-L WS-C2960S-48LPD-L WS-C2960S-24PD-L WS-C2960S-48TD-L WS-C2960S-24TD-L	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD	--	12.2(53)SE1
		GLC-EX-SMD (CPN 10-2624-01 or later only)	--	IOS 12.2(58)SE
Catalyst 2960-SF Series	2960S-F48TS-S 2960S-F24TS-S	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	15.0(2)SE

		GLC-EX-SMD (CPN 10-2624-01 or later only)		
	2960S-F48FPS-L 2960S-F48LPS-L 2960S-F24PS-L 2960S-F48TS-L 2960S-F24TS-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD (CPN 10-2624-01 or later only)	--	15.0(2)SE
Catalyst 2960-C Series	WS-C2960CG-8TC-L	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP	--	12.2(55)EX1
		GLC-EX-SMD (CPN 10-2624-01 or later only)	--	15.0(2)SE
	WS-C2960C-8TC-S	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD	--	12.2(55)EX3
		GLC-EX-SMD (CPN 10-2624-01 or later only)	--	15.0(2)SE
	WS-C2960C-	GLC-SX-MM	--	12.2(55)EX3

	8TC-L WS-C2960C-8PC-L WS-C2960C-12PC-L	GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP		
		GLC-EX-SMD (CPN 10-2624-01 or later only)	--	15.0(2)SE
Catalyst 2960-X Series	WS-C2960X-24TS-LL WS-C2960X-48TS-LL	GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-T GLC-LH-SM GLC-SX-MM	15.0(2)EX	15.0(2)EX
Catalyst 2960-X Series (continued)	WS-C2960X-24PSQ-L	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD GLC-T GLC-ZX-SM GLC-LH-SM GLC-SX-MM	15.0(2)EX	15.0(2)EX
	WS-C2960X-24PS-L WS-C2960X-24TS-L WS-C2960X-48TS-L WS-C2960X-48LPS-L	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or	15.0(2)EX	15.0(2)EX

	WS-C2960X-48FPS-L WS-C2960X-24TD-L WS-C2960X-24PD-L WS-C2960X-48TD-L WS-C2960X-48LPD-L WS-C2960X-48FPD-L	later only) GLC-ZX-SMD GLC-T GLC-ZX-SM GLC-LH-SM GLC-SX-MM CWDM-SFP		
Catalyst 2960-XR Series	WS-C2960XR-24TS-I WS-C2960XR-48TS-I WS-C2960XR-24PS-I WS-C2960XR-48LPS-I WS-C2960XR-48FPS-I WS-C2960XR-24TD-I WS-C2960XR-48TD-I WS-C2960XR-24PD-I WS-C2960XR-48LPD-I WS-C2960XR-48FPD-I	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD GLC-T GLC-ZX-SM GLC-LH-SM GLC-SX-MM CWDM-SFP	15.0(2)EX1	15.0(2)EX1
Catalyst 2970 series	WS-C2970G-24TS-E	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-ZX-SMD GLC-SX-MMD GLC-LH-SMD	--	12.1(14)EA1
Catalyst 2975 Series	WS-C2975GS-48PS-L	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	--	12.2(46)EX

		GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-SX-MMD GLC-LH-SMD		
--	--	---	--	--

Table 5 Catalyst 3500 Switches Support				
Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Dom Support	Cisco IOS Release
Catalyst 3500XL Series	WS-C3508G-XL-EN WS-C3512-XL-EN WS-C3524-XL-EN WS-C3524-PWR-XL-EN WS-C3548-XL-EN	WS-G5482	--	12.0(5)XW
		WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--	12.0(5)WC3b
Catalyst 3550 Series	WS-C3550-24-SMI WS-C3550-24-EMI WS-C3550-24-DC-SMI	WS-G5482	--	12.1(6)EA1a
		WS-G5483 WS-G5484 WS-G5486 WS-G5487	--	12.1(8)EA1b
		CWDM GBIC	--	12.1(12c)EA1
		DWDM GBIC	--	12.1(20)EA2
	WS-C3550-24-FX-SMI WS-C3550-24PWR-SMI WS-C3550-24PWR-EMI	WS-G5482 WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--	12.1(12c)EA1
		DWDM GBIC	--	12.1(20)EA2
Catalyst 3550 Series	WS-C3550-48-SMI WS-C3550-48-EMI	WS-G5482 WS-G5483 WS-G5484 WS-G5486	--	12.1(8)EA1b

(continued)		WS-G5487		
		CWDM GBIC	--	12.1(12c)EA1
		DWDM GBIC	--	12.1(20)EA2
	WS-C3550-12G WS-C3550-12T	WS-G5482	--	12.1(6)EA1
		WS-G5483 WS-G5484 WS-G5486 WS-G5487	--	12.1(8)EA1b
		CWDM GBIC	--	12.1(12c)EA1
		DWDM GBIC	--	12.1(20)EA2
Catalyst 3560 Series	WS-C3560-24PS WS-C3560-48PS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.1(19)EA1c
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.1(19)EA1c
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(20)SE3
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(20)SE3
Catalyst 3560 Series (continued)	WS-C3560G-24TS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(20)SE3
	WS-C3560G-48TS WS-C3560G-48PS WS-C3560G-24PS	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(20)SE3

		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	WS-C3560-48TS WS-C3560-24TS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(20)SE3
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(20)SE3
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	WS-C3560-8PC	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(35)SE
		GLC-ZX-SM GLC-ZX-SMD CWDM SFP GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(35)SE
Catalyst 3560 Series (continued)	WS-C3560-12PC-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	12.2(46)SE
		GLC-ZX-SM GLC-ZX-SMD	12.2(46)SE	12.2(46)SE

		CWDM SFP GLC-BX-D GLC-BX-U		
	WS-C3560V2-24PS WS-C3560V2-24TS	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(50)SE
	WS-C3560V2-48PS WS-C3560V2-48TS	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD SFP-GE-S SFP-GE-L CWDM SFP GLC-BX-D GLC-BX-U DWDM SFP	12.2(50)SE	12.2(50)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
Catalyst 3560-E Series	WS-C3560E-24TD WS-C3560E-24PD	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(35)SE2
	WS-C3560E-48TD WS-C3560E-48PD WS-C3560E-48PDF	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(35)SE2
	With CVR-X2-SFP (for X2 ports)	DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD	12.2(58)SE	12.2(58)SE

		(CPN 10-2624-01 or later only)		
	WS-C3560E-12D With CVR-X2-SFP (for X2 ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(40)EX
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(40)EX
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
Catalyst 3560-E Series (continued)	WS-C3560E-12SD	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(44)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(44)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE

		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
	WS-C3560E-12SD With CVR-X2-SFP (for X2 ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(44)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.2(44)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
Catalyst 3560-X Series	WS-C3560X-24T WS-C3560X-48T	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(53)SE
	WS-C3560X-24P WS-C3560X-48P WS-C3560X-48PF With C3KX-NM-1G and C3KX-NM-10G (slots 1 and 3) network modules	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(53)SE	12.2(53)SE

		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
	WS-C3560X-24T	GLC-SX-MM GLC-LH-SM	--	12.2(53)SE
	WS-C3560X-48T WS-C3560X-24P WS-C3560X-48P WS-C3560X-48PF With C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(53)SE	12.2(53)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
Catalyst 3560-C Series	WS-C3560CG-8TC-S WS-C3560CG-8PC-S	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP	--	12.2(55)EX
		GLC-EX-SMD (CPN 10-2624-01 or later only)	--	15.0(2)SE
	WS-C3560C-8PC-S WS-C3560C-12PC-S	GLC-SX-MM GLC-SX-MMD GLC-LH-SM GLC-LH-SMD GLC-ZX-SM	--	12.2(55)EX3

		GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP		
		GLC-EX-SMD (CPN 10-2624-01 or later only)	--	15.0(2)SE

Table 6 Catalyst 3600 Series Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3650 Series	WS-C3650-24TS WS-C3650-48TS WS-C3650-24PS WS-C3650-48PS WS-C3650-48FS WS-C3650-24TD WS-C3650-48TD WS-C3650-24PD WS-C3650-48PD WS-C3650-48FD WS-C3650-48FQ WS-C3650-48PQ WS-C3650-48TQ	GLC-T (10/100/1000) GLC-LH-SM GLC-LH-SMD GLC-SX-MM GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP DWDM SFP (add.)	XE 3.3.0SE	XE 3.3.0SE

Table 7 Catalyst 3700 Series Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3750 series	WS-C3750G-12S WS-C3750G-24TS WS-C3750G-48TS WS-C3750G-24PS WS-C3750G-48PS	GLC-T (10/100/1000)	--	12.1.(14)EA1
		GLC-SX-MM GLC-LH-SM		
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.1(14)EA1
		GLC-BX-D GLC-BX-U		
		DWDM SFP		
		DWDM SFP (add.)		
	WS-C3750-24TS WS-C3750-48TS	GLC-T (10/100/1000)	--	12.1(14)EA1
		GLC-SX-MM GLC-LH-SM		
		GLC-SX-MMD GLC-LH-SMD	12.2(46)SE	12.1(14)EA1
		GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z		
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP		
		DWDM SFP (add.)		

3750 series (continued)	WS-C3750-48PS	(10/100/1000) GLC-SX-MM GLC-LH-SM		
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z	12.2(46)SE	12.1(19)EA1c
		GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	WS-C3750-24FS-S	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(25)SEB
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP GLC-BX-D GLC-BX-U	12.2(46)SE	12.2(25)SEB
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
Catalyst 3750 series (continued)	WS-C3750-24WFS	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	--	12.2(25)FZ
		GLC-SX-MMD GLC-LH-SMD	12.2(46)SE	12.2(25)FZ

		GLC-ZX-SM GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP GLC-BX-D GLC-BX-U		
		DWDM SFP	12.2(46)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
	WS-C3750V2-24PS WS-C3750V2-24TS WS-C3750V2-48PS WS-C3750V2-48TS WS-C3750V2-24FS (uplink ports)	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(50)SE
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP GLC-BX-D GLC-BX-U DWDM SFP	12.2(50)SE	12.2(50)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
Catalyst 3750-E Series	WS-C3750E-24TD WS-C3750E-24PD WS-C3750E-48TD WS-C3750E-48PD WS-C3750E-	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(35)SE2
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D	12.2(46)SE	12.2(35)SE2

	48PDF With CVR-X2-SFP (for X2 ports)	GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z		
		DWDM SFP	12.2(44)SE	12.2(40)SE
		DWDM SFP (add.)	12.2(52)SE	12.2(52)SE
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
Catalyst 3750-X Series	WS-C3750X-24T	GLC-T (10/100/1000)	--	12.2(53)SE
	WS-C3750X-48T	GLC-SX-MM GLC-LH-SM		
	WS-C3750X-24P WS-C3750X-48P WS-C3750X-48PF	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)	12.2(53)SE	12.2(53)SE
	With C3KX-NM-1G and C3KX-NM-10G (slots 1 and 3) network modules	GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
Catalyst 3750-X Series (continued)	WS-C3750X-24T	GLC-SX-MM GLC-LH-SM	--	12.2(53)SE
	WS-C3750X-48T WS-C3750X-24P WS-C3750X-48P WS-C3750X-	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U	12.2(53)SE	12.2(53)SE

	48PF	CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)		
	With C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
	WS-C3750X-12S WS-C3750X-24S	GLC-T (10/100/1000) GLC-SX-MM GLC-LH-SM	--	12.2(55)SE5
	Client ports and uplink ports with C3KX-NM-1G and C3KX-NM-10G (slots 1 and 3) network modules	GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)	12.2(55)SE5	12.2(55)SE5
Catalyst 3750-X Series (continued)	WS-C3750X-12S WS-C3750X-24S	GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE
	Uplink ports with C3KX-NM-10G (slots 2 and 4) and C3KX-SM-10G network modules	GLC-SX-MM GLC-LH-SM	--	12.2(55)SE5
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S	12.2(55)SE5	12.2(55)SE5

		SFP-GE-L SFP-GE-Z DWDM SFP DWDM SFP (add.)		
		GLC-EX-SMD (CPN 10-2624-01 or later only)	12.2(58)SE	12.2(58)SE

Table 8 Catalyst 3800 Series Switches Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 3850 Series	C3850-NM-4-1G C3850-NM-2-10G C3850-NM-4-10G	GLC-T (10/100/1000) GLC-LH-SM GLC-LH-SMD GLC-SX-MM GLC-SX-MMD GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SM GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-T SFP-GE-Z DWDM SFP DWDM SFP (add.)	XE 3.2.0SE	XE 3.2.0SE

Table 9 Industrial Ethernet and Smart Grid Support

Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Catalyst Operating System	Cisco IOS Release

Cisco IE2000 series	IE-2000-4TS-G-L IE-2000-4TS-G-B IE-2000-4T-G-L IE-2000-4T-G-B IE-2000-8TC-G-L IE-2000-8TC-G-B IE-2000-8TC-G-E IE-2000-8TC-G-N IE-2000-16TC-G-L IE-2000-16TC-G-E IE-2000-16TC-G-X IE-2000-16TC-G-N IE-2000-16PTC-G-L IE-2000-16PTC-G-E IE-2000-16PTC-G-NX	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD SFP-GE-S SFP-GE-L SFP-GE-Z GLC-SX-MM ¹ GLC-LH-SM ¹ GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-BX-D ² GLC-BX-U ² CWDM SFP ² DWDM SFP ² DWDM SFP (add.) ²	--	15.0(1)EY
Cisco IE2000U series	IE 2000U-4TS-G IE 2000U-8TC-G IE 2000U-16TC-G IE 2000U-16TC-G-X IE 2000U-16TC-GP	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z GLC-EX-SMD CWDM-SFP	--	15.0(2)EH
Cisco IE3000	IE-3000-4TC	GLC-SX-	--	12.2(44)EX

series	IE-3000-8TC	MM-RGD GLC-LX- SM-RGD GLC-ZX- SM-RGD		
		GLC-BX-D GLC-BX-U CWDM SFP	--	12.2(50)SE
		GLC-LH- SMD GLC-EX- SMD GLC-ZX- SMD	--	15.0(2)SE
Cisco IE3010 series	IE-3010-24TC IE-3010-16S-8PC	GLC-SX- MM-RGD GLC-LX- SM-RGD GLC-ZX- SM-RGD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP GLC-SX- MMD	--	12.2(53)EZ
		GLC-LH- SMD GLC-EX- SMD GLC-ZX- SMD	--	15.0(2)SE
Cisco 2500 Connected Grid Switch Series	CGS-2520-24TC CGS-2520-16S-8PC	GLC-SX- MM-RGD GLC-LX- SM-RGD GLC-ZX- SM-RGD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L	--	12.2(53)EX

		GLC-EX-SMD SFP-GE-Z CWDM SFP		
Cisco 2000 Connected Grid Router Series	CGR 2010	GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD	--	15.1(1)T

¹Only Version -03 or later is supported.

²Only Version -02 or later is supported.

Table 10 Catalyst 4500 and Catalyst 4900 Switches Support				
Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			Cisco IOS Support	DOM Support
Catalyst 4500 series	WS-X4013	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CDWM GBIC	--	--
	WS-X4013+	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CDWM GBIC	12.1(19)EW	--
		DWDM GBIC	12.1(19)EW	12.1(19)EW
	WS-X4013+TS	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(20)EWA	--

		GLC-BX-D GLC-BX-U CWDM SFP	12.2(20)EWA	12.2(20)EWA
		DWDM SFP	12.2(37)SG	12.2(37)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
	WS- X4013+10GE	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(25)SG	--
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(25)SG	12.2(25)SG
		DWDM SFP	12.2(37)SG	12.2(37)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
Catalyst 4500 series (continued)	WS-X4748-SFP-E WS-X4724-SFP-E WS-X4712-SFP-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-EX-SMD GLC-ZX-SMD GLC-LH-SMD GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP SFP-GE-S SFP-GE-L SFP-GE-Z DWDM SFP	15.2(1)E	15.2(1)E
	WS-X4014	WS-G5483	12.1(13)EW	--

	WS-X4232-GB-RJ	WS-G5484 WS-G5486 WS-G5487	12.1(8a)EW	--
	WS-X4306-GB	CWDM GBIC	12.1(12c)EW	--
	WS-X4412-2GB-T	DWDM GBIC	12.1(19)EW	12.1(19)EW
Catalyst 4500 series (continued)	WS-X4418-GB	WS-G5484 WS-G5486 WS-G5487	12.1(8a)EW	--
		CWDM GBIC	12.1(12c)EW	--
		DWDM GBIC	12.1(19)EW	12.2(19)EW
	WS-X4302-GB	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	12.1(19)EW	--
		DWDM GBIC	12.1(19)EW	12.2(19)EW
	WS-X4448-GB-SFP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(20)EW	--
		CWDM SFP	12.2(20)EW	12.2(20)EW
		GLC-BX-D GLC-BX-U	12.2(20)EWA	12.2(20)EWA
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-	12.2(25)EWA	12.2(25)EWA

		SMD	10	10
	WS-X4506-GB-T	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(20)EWA	--
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(20)EWA	12.2(20)EWA
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
Catalyst 4500 series (continued)	WS-X4515	WS-G5483	12.1(13)EW	--
		WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	12.1(12c)EW	--
		DWDM GBIC	12.1(19)EW	12.1(19)EW
	WS-X4516	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	12.2(18)EW	--
		DWDM GBIC	12.2(18)EW	12.2(18)EW
	WS-X4516-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-	12.2(25)EWA	--

		MMD GLC-LH-SMD		
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(25)EWA	12.2(25)EWA
		DWDM SFP	12.2(37)SG	12.2(37)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
		GLC-ZX-SMD	12.2(25)EWA 10	12.2(25)EWA 10
	WS-X45-SUP6-E WS-X4606-X2 with CVR-X2-SFP Twin Gig converter	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(40)SG	--
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(40)SG	12.2(40)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-SMD	12.2(40)SG	12.2(40)SG
Catalyst 4500 series (continued)	WS-X4624-SFP-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD	12.2(44)SG	--

		GLC-LH-SMD		
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(44)SG	12.2(44)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-SMD	12.2(44)SG1	12.2(44)SG1
	WS-X45-SUP6L-E with CVR-X2-SFP Twin Gig converter	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(52)SG	--
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(52)SG	12.2(52)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
		GLC-EX-SMD GLC-ZX-SMD	15.1(1)SG	15.1(1)SG
Catalyst 4500 series (continued)	WS-X4612-SFP-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	12.2(54)SG	--

		GLC-SX-MMD GLC-LH-SMD		
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(54)SG	12.2(54)SG
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-SMD	12.2(44)SG1	12.2(44)SG1
	WS-X4640- CSFP-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	15.0(2)SG	--
		GLC-BX-D GLC-2BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-ZX-SMD	15.0(2)SG	15.0(2)SG
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
Catalyst	WS-X4712-	GLC-T	3.1.0SG	--

4500 series (continued)	SFP+E WS-X45-SUP7-E	(1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD		
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.1.0SG	3.1.0SG
		GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD	3.4.1SG	3.4.1SG
	WS-X45-SUP7L-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	3.2.0XO	--
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.2.0XO	3.2.0XO
		GLC-EX-SMD (CPN 10-2624-01	3.4.1SG	3.4.1SG

		or later only) GLC-ZX-SMD		
Catalyst 4500 series (continued)	WS-X45-SUP8-E	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD	3.3.0XO	--
		GLC-LH-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD	3.3.0XO	3.3.0XO
Catalyst 4500-X Series	WS-C4500X-32SFP+ WS-C4500X-F-32SFP+ WS-C4500X-40X-ES C4KX-NM-8SFP+	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	3.3.0SG	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	3.3.0SG	--
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	3.3.0SG	3.3.0SG

		DWDM SFP (add.)		
		GLC-EX-SMD (CPN 10-2624-01 or later only)	3.4.1SG	3.4.1SG
	WS-C4500X-16SFP+ WS-C4500X-F-16SFP+ WS-C4500X-24X-ES	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	3.3.1(SG	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	3.3.1SG	--
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	3.3.1SG	3.3.1SG
		GLC-EX-SMD (CPN 10-2624-01 or later only)	3.4.1SG	3.4.1SG
Catalyst 4900 Series	WS-C4912G	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--	--
	WS-C4948	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	12.2(20)EWA	--

		GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-ZX-SMD		
		GLC-BX-D GLC-BX-U CWDM SFP	12.2(20)EWA	12.2(20)EWA
		DWDM SFP	12.2(37)SG	12.2(37)SG
		DWDM (add.)	12.2(53)SG3	12.2(53)SG3
	WS-4928-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(46)SG	--
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(46)SG	12.2(46)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
	Catalyst 4900 Series (continued)	WS-C4948E GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(54)SG	--

		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(54)SG	12.2(54)SG
		DWDM SFP (add.) GLC-EX-SMD (CPN 10-2624-01 or later only) GLC-ZX-SMD	12.2(53)SG3	12.2(53)SG3
	WS-X4908 with CVR-X2-SFP Twin Gig converter in a WS-C4900M	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	12.2(40)X0 or 12.2(44)SG	--
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(40)X0 or 12.2(44)SG	12.2(40)X0 or 12.2(44)SG
		DWDM SFP (add.)	12.2(53)SG3	12.2(53)SG3
		GLC-EX-SMD (CPN 10-2624-01 or later only)	15.1(1)SG	15.1(1)SG
		GLC-ZX-SMD	12.2(40)XO	12.2(40)XO

Table 11 Catalyst 6500 Series Switches Support

Platform	Switch or	Transceiver Module	Minimum Software Release Required
----------	--------------	-----------------------	-----------------------------------

	Module				
			Catalyst Operating System	Cisco IOS Release	DOM Support
Catalyst 6500 Series	WS-X6K-SUP1-2GE WS-X6K-SUP1A-2GE WS-X6K-SUP1A-MSFC WS-X6K-SUP1A-MSFC2 WS-X6K-SUP1A-PFC WS-X6K-SUP2U-MSFC2 WS-X6K-S2-PFC2	WS-G5483	7.2	12.1(13)E	--
		WS-G5484 WS-G5486 WS-G5487	Please see release notes for details	Please see release notes for details	--
		CWDM GBIC	7.2	12.1(13)E	--
	WS-X6K-SUP2-MSFC2 WS-X6K-SUP2U-PFC2 WS-X6408-GBIC WS-X6408A-GBIC	WS-G5483	7.2	12.1(13)E	--
		WS-G5484 WS-G5486 WS-G5487	Please see release notes for details	Please see release notes for details	--
		CWDM GBIC	7.2	12.1(13)E	--
		DWDM GBIC	8.3.1	12.2(17a)SX	--

	WS-X6416-GBIC				
	WS-X6516-GBIC				
	WS-X6816-GBIC				
	WS-X6516A-GBIC	WS-G5483	7.5.1	12.1(19)E1	--
		WS-G5484 WS-G5486 WS-G5487	Please see release notes for details	Please see release notes for details	--
		CWDM GBIC	7.5.1	12.1(19)E1	--
		DWDM GBIC	8.3.1	12.2(17a)SX	--
	WS-SUP720	GLC-T(1000BASE-T)	8.3.1	12.2(17a)SX	--
		GLC-SX-MM	8.1.1	12.2(14)SX	--
		GLC-LH-SM	8.1.1	12.2(17a)SX	--
		GLC-ZX-SM	8.2	12.2(17d)SXB1	--
		GLC-BX-D	8.4.1	12.2(18)SXE1	12.2(18)SXE1
		GLC-BX-U	8.4.1	12.2(18)SXE1	12.2(18)SXE1
		CWDM SFP	8.3.1	12.2(17a)SX	12.2(18)SXE
		DWDM SFP ³	--	12.2(33)SXH	12.2(33)SXH
Catalyst 6500 Series (continued)	WS-SUP720-3B	GLC-T(1000BASE-T)	8.3.2	12.2(17d)SXB1	--
	WS-SUP720-3BXL	GLC-SX-MM	8.3.2	12.2(17d)SXB1	--
		GLC-LH-SM	8.3.2	12.2(17d)SXB1	--
		GLC-ZX-SM	8.4.1	12.2(18)SXE1	12.2(18)SXE1
		GLC-BX-D	8.4.1	12.2(18)SXE1	12.2(18)SXE1
		GLC-BX-U	8.3.2	12.2(17d)SXB1	12.2(18)SXE
		CWDM SFP	--	12.2(33)SXH	12.2(33)SXH
		DWDM SFP ¹	--	12.2(17d)SXB1	--

		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	12.2(17d)SXB1	--
	WS-SUP32-GE-3B	GLC-T (1000BASE-T)	8.4(1)	12.2(18)SXF	--
	WS-SUP32-10GE-3B	GLC-SX-MM	8.4(1)	12.2(18)SXF	--
		GLC-LH-SM	8.4(1)	12.2(18)SXF	--
		GLC-ZX-SM	8.4(1)	12.2(18)SXF	12.2(18)SXF
		GLC-BX-D	8.4(1)	12.2(18)SXF	12.2(18)SXF
		GLC-BX-U	8.4(1)	12.2(18)SXF	12.2(18)SXF
		CWDM SFP	--	12.2(33)SXH	12.2(33)SXH
		DWDM SFP ¹	--	12.2(18)SXF	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	12.2(18)SXF	--
	WS-SUP32-GE-PISA	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP ¹ GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--	12.2(18)ZY	--
Catalyst 6500 Series (continued)	VS-S720-10G-3C VS-S720-10G-3CXL	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D	--	12.2(33)SXH	-- -- -- 12.2(33)SXH 12.2(33)SXH

		GLC-BX-U CWDM SFP DWDM SFP ¹ GLC-SX- MMD GLC-LH- SMD GLC-ZX- SMD			12.2(33)SXH 12.2(33)SXH -- --
	WS- X6724- SFP WS- X6748- SFP	GLC-T (1000BASE- T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP ¹ GLC-SX- MMD GLC-LH- SMD GLC-ZX- SMD	8.3.1 8.1.1 8.1.1 8.2 8.4.1 8.4.1 8.3.1 -- -- --	12.2(17a)SX 12.2(14)SX 12.2(17a)SX 12.2(17d)SXB1 12.2(18)SXE1 12.2(18)SXE1 12.2(17a)SX 12.2(33)SXH - 12.2(14)SX 12.2(17a)SX	--
Catalyst 6500 Series (continued)	VS-S2T- 10G VS-S2T- 10G-XL WS- X6824- SFP-2T WS- X6824- SFP- 2TXL WS- X6848- SFP-2T WS- X6848- SFP- 2TXL	GLC-T (1000BASE- T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM-SFP DWDM-SFP ¹ GLC-SX- MMD GLC-LH- SMD GLC-ZX- SMD	--	12.2(50)SY	--
	WS- X6904-	GLC-T (1000BASE-	--	15.1(1)SY	--

	40G-2T WS- X6904- 40G- 2TXL	T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM-SFP DWDM-SFP ¹ GLC-SX- MMD GLC-LH- SMD GLC-ZX- SMD			
--	---	--	--	--	--

³Does not include support for the DWDM SFP transceivers (8 additional wavelengths). See [Table 1](#) for specific model numbers.

Table 12 Catalyst 6800 Series Switches Support				
Platform	Switch or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Catalyst 6800 Series	C6800IA-48FPD C6800IA-48TD	GLC-BX-D GLC-BX-U GLC-LH-SMD GLC-SX-MMD GLC-T GLC-SX-MM	15.1(2)SY2	15.1(2)SY2
	C6880-X	GLC-LH-SMD GLC-SX-MMD GLC-EX-SMD GLC-ZX-SMD GLC-T GLC-ZX-SM GLC-LH-SM GLC-SX-MM	15.1(2)SY1	15.1(2)SY1

Table 13 Data Center and Blade Switching Support			
			Minimum Software Release R

Platform	Switch or Module	Transceiver Module	DOM support	Cisco IOS OS Release
Cisco Catalyst 2350 Series	2350-48TD-S 2350-48TD-SD (with CVR-X2-SFP TwinGig converter)	GLC-T GLC-SX-MM GLC-SX-MMD	--	Cisco IOS 12.2(46)EY
Cisco Catalyst 2360 Series	2360-48TD-S	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(53)EY
Cisco Catalyst 3000 and 3100 Blade Switches	WS-CBS3020-HPQ	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(35)SE
	WS-CBS3030-DEL WS-CBS3040-FSC	GLC-T (1000BASE-T) GLC-SX-MM GLC-SX-MMD	--	Cisco IOS 12.2(35)SE
	WS-CBS-3120G-S WS-CBS-3130G-S (with CVR-X2-SFP TwinGig converter)	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(40)EX
	WS-CBS3032-DEL (with CVR-X2-SFP TwinGig converter)	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(40)EX
	WS-CBS3110X-S (with CVR-X2-SFP TwinGig converter)	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	Cisco IOS 12.2(52)SE
Cisco Nexus 2000 Series	N2K-C2232PP-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	NX-OS 4.2
Cisco Nexus 3000 Series	N3K-C3064PQ	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	NX-OS 5.0(3)U1(1)

	N3K-C3064PQ-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	NX-OS 5.0
	N3K-C3048TP-1GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	NX-OS 5.0(3)U2(2)
Cisco Nexus 4000 Series	N4K-4001I-XPX	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	NX-OS 4.1
Cisco Nexus 5000 Series	N5K-C5010P-BF N5K-C5020P-BF	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM SFP-GE-T (1000BASE-T)	--	NX-OS 4.0(1a)N1(1)
		SFP-GE-S SFP-GE-L GLC-SX-MMD GLC-LH-SMD	NX-OS 4.0(1a)N1(1)	NX-OS 4.0(1a)N1(1)
	N5K-C5548P-FA N5K-C5548UP-FA N5KC5596UP-FA N55-M16P N55-M8P8FP N55-M16UP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM SFP-GE-T (1000BASE-T)	--	NX-OS 5.0(3)N1(1)
Cisco Unified Computing System	N10-S6100 N10-S6200 N10-E0440 N10-E0600 N20-I6584	SFP-GE-S SFP-GE-L GLC-SX-MMD GLC-LH-SMD	UCS Manager v1.3	UCS Manager
		GLC-SX-MM GLC-LH-SM GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T)	--	UCS Manager
	UCS-FI-6248UP	SFP-GE-S	UCS Manager	UCS Manager

	UCS-FI-E16UP UCS-IOM-2208XP	SFP-GE-L GLC-SX-MMD GLC-LH-SMD	v2.0(1)	v2.0(1)
		GLC-SX-MM GLC-LH-SM GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T)	--	UCS Mana v2.0(1)
Cisco Nexus 7000 Series	N7K-M148GS-11	SFP-GE-S GLC-SX-MMD GLC-SX-MM SFP-GE-L GLC-LH-SMD GLC-LH-SM SFP-GE-Z GLC-ZX-SM	NX-OS 4.1(2) NX-OS 4.1(2) -- NX-OS 4.1(2) NX-OS 4.1(2) -- NX-OS 4.1(2) --	NX-OS 4.1
		GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T) CWDM SFP DWDM SFP	-- -- -- NX-OS 4.2(1) NX-OS 4.2(1)	NX-OS 4.2
		GLC-BX-D GLC-BX-U	NX-OS 5.2(1) NX-OS 5.2(1)	NX-OS 5.2
		GLC-EX-SMD GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2
Cisco Nexus 7000 Series (continued)	N7K-M148GS-11L	SFP-GE-S GLC-SX-MMD GLC-SX-MM SFP-GE-L GLC-LH-SMD GLC-LH-SM SFP-GE-Z GLC-ZX-SM	NX-OS 5.0(2a) NX-OS 5.0(2a) -- NX-OS 5.0(2a) NX-OS 5.0(2a) -- NX-OS 5.0(2a) --	NX-OS 5.0
		GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T) CWDM SFP DWDM SFP	-- -- -- NX-OS 5.0(2a) NX-OS 5.0(2a)	
		GLC-BX-D GLC-BX-U	NX-OS 5.2(1) NX-OS 5.2(1)	NX-OS 5.2

		GLC-EX-SMD GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2
	N7K-F132XP-15	SFP-GE-S GLC-SX-MMD GLC-SX-MM SFP-GE-L GLC-LH-SMD GLC-LH-SM SFP-GE-Z GLC-ZX-SM GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T)	NX-OS 5.1(1) NX-OS 5.1(1) -- NX-OS 5.1(1) NX-OS 5.1(1) -- NX-OS 5.1(1) -- -- --	NX-OS 5.1
		GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2
Cisco Nexus 7000 Series (continued)	N7K-F248XP-25	GLC-T (1000BASE-T) SFP-GE-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	NX-OS 6.0
		GLC-SX-MMD SFP-GE-S GLC-LH-SMD SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	NX-OS 6.0	NX-OS 6.0
		GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2
	N7K-F248XP-25E	GLC-T (1000BASE-T) SFP-GE-T(1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--	NX-OS 6.1
		GLC-SX-MMD SFP-GE-S GLC-LH-SMD SFP-GE-L SFP-GE-Z GLC-BX-D	NX-OS 6.1(2)	NX-OS 6.1

		GLC-BX-U CWDM SFP DWDM SFP		
		GLC-ZX-SMD	NX-OS 6.2(2)	NX-OS 6.2
Cisco Nexus 7000 Series (continued)	N77-F348XP-23	GLC-T SFP-GE-T	--	NX-OS 6.2
		GLC-TE	--	NX-OS 6.2
		GLC-SX-MM SFP-GE-S GLC-SX-MMD GLC-LH-SM SFP-GE-L GLC-LH-SMD GLC-EX-SMD GLC-ZX-SM SFP-GE-Z GLC-ZX-SMD GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP	NX-OS 6.2(8)	NX-OS 6.2
Cisco Nexus 9000 Series (Modular 9500) NX-OS Mode	N9K-X9564PX	GLC-SX-MM GLC-LH-SM GLC-T (1000BASE-T)	--	6.1(2)I2(1)
		GLC-SX-MMD GLC-LH-SMD	6.1(2)I2(1)	6.1(2)I2(1)
		SFP-GE-T	-	6.1(2)I3(1)
	N9K-X9464PX	GLC-SX-MM GLC-LH-SM GLC-T (1000BASE-T)	--	6.1(2)I2(2a)
		GLC-SX-MMD GLC-LH-SMD	6.1(2)I2(2a)	6.1(2)I2(2a)
		SFP-GE-T	-	6.1(2)I3(1)
Cisco Nexus 9000 Series (Fixed)	N9K-C9396PX	GLC-SX-MM GLC-T (1000BASE-T)	--	6.1(2)I2(1)
		GLC-SX-MMD GLC-LH-SMD	6.1(2)I2(1)	6.1(2)I2(1)
		SFP-GE-T	-	6.1(2)I3(1)

9300) NX-OS Mode	N9K-C9372PX	GLC-SX-MM GLC-T (1000BASE-T) SFP-GE-T	-	6.1(2)I3(1)
		GLC-SX-MMD GLC-LH-SMD	6.1(2)I3(1)	6.1(2)I3(1)
Cisco Nexus 9000 Series (Fixed 9300) ACI Mode	N9K-C9396PX	GLC-T (1000BASE-T) GLC-SX-MMD	--	ACI-N9KD
Cisco CSS 11500 Series	CSS11506-2AC CSS11506-2DC CSS11503-AC CSS11503-DC CSS11501 CSS5-SCM-2GE CSS5-IOM-2GE	GLC-T GLC-SX-MM GLC-LH-SM	--	WebNS 7.5
Cisco MDS 9000 Series	Please refer to: http://www/en/US/prod/collateral/ps4159/ps6409/ps4358/product_data_sheet09186a00801b			

Table 14 Router Support			
Platform	Switch or Module	Transceiver Module	Minimum Software DOM Support
Cisco 892F Series	CISCO892F-K9 CISCO892FW-K9	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
Cisco 1921 Series Router	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--

		CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	
	EHWIC-1GE-SFP-CU	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
Cisco 1941 Series Router	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
	EHWIC-1GE-SFP-CU	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
Cisco 2600 Series Router	NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC GLC-ZX-SMD	--
	NME-XD-24ES-1S-P NME-XD-48ES-2S-P	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--

		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	
Cisco 2800 Series Router	NME-XD-24ES-1S-P NME-XD-48ES-2S-P	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
Cisco 2900 Series Router	Cisco 2921 Cisco 2951	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
Cisco 2900 Series Router (continued)	SM-D-ES3G-48-P SM-D-ES3-48-P SM-D-ES2-48	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP	--

		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	
	EHWIC-1GE-SFP-CU	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
Cisco 3200 Series Rugged Routers	Cisco 3270	GLC-SX-MM-RGD GLC-LX-SM-RGD	--
Cisco 3600 Series Router	NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--
Cisco 3700 Series Router	NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--
	NME-XD-24ES-1S-P NME-XD-48ES-2S-P	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD	--
Cisco 3800 Series Router	NM-1GE	WS-G5483 WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--
	NME-XD-24ES-1S-P NME-XD-48ES-2S-P	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--

		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	
	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
	Cisco 3825	GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
	Cisco 3845	GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
Cisco 3900 Series Router	Cisco 3925 Cisco 3945	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
	HWIC-1GE-SFP	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
	SM-D-ES3G-	GLC-T	--

	48-P SM-D-ES3-48-P SM-D-ES2-48	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	
	EHWIC-1GE-SFP-CU	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
Cisco 4400 Series Router	Cisco 4451-X	GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-U GLC-BX-D CWDM SFP DWDM SFP	--
		GLC-LH-SMD GLC-SX-MMD	--
		GLC-ZX-SMD	--
Cisco 6400 Universal Access Router	C6400-NRP-2SV	WS-G5484 WS-G5486 WS-G5487	--
Cisco 7200 Series Router The Cisco 7200 series router supports	NPE-G1	WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--
	Cisco 7201	GLC-SX-MM	--

multiple parallel release branches. Where several releases are grouped together, they provide support for all transceivers in the corresponding group.		GLC-SX-MMD	
		SFP-GE-T	--
		SFP-GE-S SFP-GE-L GLC-LH-SMD SFP-GE-Z CWDM SFP	--
	NPE-G2	GLC-SX-MM GLC-SX-MMD	--
		SFP-GE-S SFP-GE-L GLC-LH-SMD SFP-GE-Z CWDM SFP	--
	C7200-I/O-GE+E	WS-G5484 WS-G5486 WS-G5487	--
	PA-GE	WS-G5484 WS-G5486 WS-G5487	--
Cisco uBR7200 Series	uBR7200-NPE-G1	WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--
	uBR7200-NPE-G2	GLC-SX-MMD GLC-LH-SMD SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP	12.2SB
Cisco 7300 Series Router	CISCO7301	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
	7300-NSE-100	WS-G5484 WS-G5486	--

		WS-G5487	
		WS-G5483 CWDM GBIC	--
	7304-NPE-G100	GLC-SX-MM GLC-LH-SM GLC-ZX-SM CWDM SFP	--
	7300-NSE-150	GLC-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP	12.2(31)SB2
Cisco 7500 Series Router	GEIP	WS-G5484	--
	GEIP+	WS-G5486 WS-G5487	
Cisco 7600 Series Router	OSM-1CHOC12/T1-SI OSM-1CHOC12/T3-SI OSM-2OC12-ATM-MM OSM-2OC12-ATM-SI OSM-2OC12-ATM-MM+ OSM-2OC12-ATM-SI+ OSM-4OC3-POS-SI OSM-4OC3-POS-SI+ OSM-4OC12-POS-SI OSM-4OC12-	WS-G5484 WS-G5486 WS-G5487 CWDM GBIC	--

	POS-SI+ OSM-8OC3- POS-MM OSM-8OC3- POS-SI OSM-8OC3- POS-SL OSM-8OC3- POS-SL+ OSM-8OC3- POS-SI+ OSM-16OC3- POS-MM OSM-16OC3- POS-SI OSM-16OC3- POS-SL OSM-16OC3- POS-SI+ OSM-20C12- POS-MM OSM-20C12- POS-SI OSM-20C12- POS-SL OSM-20C12- POS-SI+ OSM-20C12- POS-MM+ OSM4OC12- POS-MM OSM4OC12- POS-SI OSM4OC12- POS-SL OSM4OC12- POS-SI+ OSM-10C48- POS-SI OSM-10C48- POS-SL OSM-10C48- POS-SS OSM-10C48- POS-SS+ OSM-10C48-		
--	---	--	--

	POS-SI+ OSM-1OC48- POS-SL+ OSM- 2OC48/1DPT- SS OSM- 2OC48/1DPT- SI OSM- 2OC48/1DPT- SL OSM-2+4GE- WAN+ OSM-4GE- WAN-GBIC		
Cisco 7600 Series Router (continued)	WS-SUP720 WS-SUP720-3B WS-SUP720-3BXL	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
		CWDM SFP	12.2(33)SRA
	WS-SUP32-GE-3B	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	--
		GLC-BX-D GLC-BX-U	12.2(33)SRA
		CWDM SFP	12.2(33)SRB
		DWDM SFP	12.2(33)SRE
	WS-X6724-SFP WS-X6748-SFP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-BX-D GLC-BX-U CWDM SFP GLC-SX-MMD	--

		GLC-LH-SMD GLC-ZX-SMD	
		SFP-GE-T (1000BASE-T) SFP-GE-S SFP-GE-L SFP-GE-Z	--
		DWDM SFP	--
Cisco 7600 Series Router (continued)	RSP720-3C-GE RSP720-3CXL-GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(33)SRE1
		SFP-GE-T (1000BASE-T)	--
		GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP SFP-GE-S SFP-GE-L	12.2(33)SRE1
	RSP720-10GE	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM GLC-ZX-SM SFP-GE-T (1000BASE-T)	--
		GLC-BX-D GLC-BX-U SFP-GE-S SFP-GE-L GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(33)SRC
		CWDM SFP DWDM SFP	12.2(33)SRE1
	7600-ES20-GE3CXL 7600-ES20-GE3C	SFP-GE-S SFP-GE-L SFP-GE-Z GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	12.2(33)SRB
		SFP-GE-T	--

		CWDM SFP	12.2(33)SRB3
		GLC-BX-D GLC-BX-U DWDM SFP	12.2(33)SRD
		DWDM SFP (add.)	12.2(33)SRE
Cisco 7600 Series Router (continued)	7600-ES+20G3C 7600-ES+20G3CXL 7600-ES+40G3C 7600-ES+40G3CXL	SFP-GE-T	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(33)SRD
		DWDM SFP (add.)	12.2(33)SRE
	76-ES+T-20G 76-ES+T-40G	SFP-GE-T	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	12.2(33)SRD3
		DWDM SFP (add.)	12.2(33)SRE
	76-ES+XC-20G3C 76-ES+XC-20G3CXL 76-ES+XC-40G3C 76-ES+XC-40G3CXL	SFP-GE-T	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	12.2(33)SRE
Cisco 10000	ESR-1GE	WS-G5484	--

Series Router		WS-G5486 WS-G5487	
	ESR-HH-1GE	SFP-GE-T	--
		SFP-GE-S SFP-GE-L SFP-GE-Z	12.0(23)S
Cisco uBR10000 Series Router	UBR10-1GE	WS-G5484 WS-G5486 WS-G5487	--
	ESR-HH-1GE	SFP-GE-T	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD SFP-GE-S SFP-GE-L SFP-GE-Z	12.3(13)BC
Cisco RF Gateway Series	RFGW-X4516-10GE	SFP-GE-S SFP-GE-L	12.2(44)SQ
	RFGW-DS48	SFP-GE-T	--
		SFP-GE-S SFP-GE-L	12.2(44)SQ
Cisco 10700 Series Internet Router	10720-GE-FE-TX 10720-GE-FE-TX-B	SFP-GE-T	--
		SFP-GE-S SFP-GE-L SFP-GE-Z	12.0(26)S
		CWDM SFP	12.0(31)S
Cisco 12000 Series Router	10x1GE-SFP-LC-B	GLC-SX-MM GLC-LH-SM	--
	4GE-SFP-LC	GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD CWDM SFP	
	EPA-3GE-SX/LH-LC	GLC-SX-MM GLC-LH-SM GLC-ZX-SM	--
Shared Port	SPA-2X1GE	SFP-GE-T	SPA software support is determined by the

Adapters (SPAs)	SPA-5X1GE SPA-8X1GE SPA-10X1GE SPA-5X1GE-V2 SPA-8X1GE-V2 SPA-10X1GE-V2	SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	Refer to the SPA release notes for the corre
	SPA-2X1GE-V2	SFP-GE-S SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	
CRS Router Series	CRS-16-RP	GLC-LH-SM GLC-LH-SMD	--
	CRS-16-RP-B	GLC-LH-SM GLC-LH-SMD	--
	CRS-FCC-SC-22GE	GLC-LH-SM GLC-LH-SMD	--
	42-1GE 20-1GE-FLEX	SFP-GE-T (1000BASE-T)	--
		SFP-GE-S GLC-SX-MMD SFP-GE-L GLC-LH-SMD SFP-GE-Z	XR 3.8.1
ASR 901 Series Router	CRS-8-PRP-6G CRS-8-PRP-12G	GLC-LH-SM GLC-LH-SMD	--
	A901-12C-F-D A901-12-C-FT-D	GLC-T SFP-GE-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MM-RGD GLC-LX-SM-RGD	--
		SFP-GE-S SFP-GE-L SFP-GE-Z	15.1(2)SNI

		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U GLC-EX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	15.2(2)SNI
ASR 901 Series Router (continued)	A901-4C-F-D A901-4-C-FT-D A901-6CZ-F-D A901-6-CZ-FT-D A901-6CZ-F-A A901-6-CZ-FT-A	GLC-T SFP-GE-T GLC-SX-MM GLC-LH-SM GLC-ZX-SM GLC-SX-MM-RGD GLC-LX-SM-RGD	--
		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD GLC-BX-D GLC-BX-U GLC-EX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	15.2(2)SNH1
Cisco ASR 903 Series	A900-IMA8S	SFP-GE-T GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD	--
		GLC-BX-D GLC-BX-U GLC-EX-SMD	XE 3.5.0S
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	XE 3.6.0S
ASR 1000 Series Router	ASR1001	SFP-GE-T	--
	ASR1002	SFP-GE-S	XE 2.1

	ASR1002-F ASR1002-X	SFP-GE-L SFP-GE-Z CWDM SFP DWDM SFP	
		GLC-BX-D GLC-BX-U	XE 2.5
		GLC-SX-MMD GLC-LH-SMD GLC-ZX-SMD	XE 3.4S
		GLC-EX-SMD	XE 3.5S
	ASR 1000 platform with SPA cards	Software support on the ASR 1000 modular platforms is determined by t Refer to the SPA release notes for the correct software release. http://www.cisco.com/en/US/docs/interfaces_modules/shared_port_adap	
ASR 9000 Series Router	A9K-40GE-B A9K-40GE-E	SFP-GE-T (10/100/1000)	--
		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP	XR 3.7.3
		DWDM SFP (add.)	XR 3.9.0
		GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	XR 4.1.1
ASR 9000 Series Router (continued)	A9K-2T20GE-B A9K-2T20GE-E A9K-2T20GE-L A9K-40GE-L	SFP-GE-T (10/100/1000)	--
		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.)	XR 3.9.0
		GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	XR 4.1.1
	A9K-MPA- 20X1GE	SFP-GE-T (10/100/1000) GLC-LH-SM	--

		SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	XR 4.2.0
	A9K-RSP440-TR	SFP-GE-T (10/100/1000)	--
	A9K-RSP440-SE	SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U CWDM SFP DWDM SFP DWDM SFP (add.) GLC-SX-MMD GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD	XR 4.2.1
ASR 9000 Series Router (EOBC-supported optics)	ASR-9001	SFP-GE-S	XR 4.2.1
	ASR-9001-S	GLC-SX-MMD GLC-LH-SMD	XR 4.3.0
	ASR-9922-RP-SE	SFP-GE-S GLC-SX-MMD	XR 4.3.1
	ASR-9922-RP-TR	GLC-LH-SMD	
	A9K-RSP440-TR	SFP-GE-S	XR 4.2.1
	A9K-RSP440-SE	GLC-SX-MMD GLC-LH-SMD	XR 4.3.0 XR 4.2.3
ASR9000v Series Router	ASR-9000V-AC ASR-9000V-DC-A ASR-9000V-DC-E	SFP-GE-T SFP-GE-S SFP-GE-L SFP-GE-Z GLC-BX-D GLC-BX-U GLC-SX-MMD	XR 5.1.0

		GLC-LH-SMD GLC-EX-SMD GLC-ZX-SMD CWDM SFP DWDM SFP DWDM SFP (add.)	
		GLC-T	--
Cisco MWR 2941 Mobile Wireless Routers	MWR-2941-DC	GLC-SX-MMD GLC-LH-SMD SFP-GE-S SFP-GE-L SFP-GE-Z	12.4(19)MR1
		GLC-SX-MM-RGD GLC-LX-SM-RGD GLC-ZX-SM-RGD	--
		SFP-GE-T	--
		CWDM SFP DWDM SFP	12.4(19)MR3/ 12.2(33)MRA
		GLC-BX-D GLC-BX-U	12.2(33)MRB/ 12.4(20)MRA
		GLC-EX-SMD	15.1(01)MR

Table 15 Appliance Support				
			Minimum Software Release Required	
Platform	Switch or Module	Transceiver Module	DOM Support	Cisco IOS Release
ASA5500 Series appliances	SSM-4GE	GLC-SX-MM GLC-LH-SM GLC-SX-MMD GLC-LH-SMD	--	ASA 7.0
NAM 2200 Series appliances	NAM2204-SFP	GLC-T (1000BASE-T) GLC-SX-MM GLC-LH-SM	--	NAM 4.0

Table 16 Wireless LAN Controllers Support				
Platform	Controller or Module	Transceiver Module	Minimum Software Release Required	
			DOM Support	Cisco IOS Release
Cisco 5700 WLC Series	AIR-CT5760-25-K9	GLC-T (10/100/1000)	XE 3.2.0SE	XE 3.2.0SE
	AIR-CT5760-50-K9	GLC-LH-SM		
	AIR-CT5760-100-K9	GLC-LH-SMD		
	AIR-CT5760-250-K9	GLC-SX-MM		
	AIR-CT5760-500-K9	GLC-SX-MMD		
	AIR-CT5760-1K-K9	GLC-EX-SMD		
	AIR-CT5760-1K-K9	(CPN 10-2624-01 or later only)		
	AIR-CT5760-1K-K9	GLC-ZX-SM		
	AIR-CT5760-1K-K9	GLC-ZX-SMD		
	AIR-CT5760-1K-K9	GLC-BX-D		
	AIR-CT5760-1K-K9	GLC-BX-U		
	AIR-CT5760-1K-K9	CWDM SFP		
	AIR-CT5760-1K-K9	SFP-GE-S		
	AIR-CT5760-1K-K9	SFP-GE-L		
	AIR-CT5760-1K-K9	SFP-GE-T		
	AIR-CT5760-1K-K9	SFP-GE-Z		
	AIR-CT5760-1K-K9	DWDM SFP		
	AIR-CT5760-1K-K9	DWDM SFP (add.)		

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as an RSS feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service. Cisco currently supports RSS Version 2.0.

